

SmartPro 230V 1.5kVA 900W Line-Interactive UPS, 2U Rack/Tower, LCD, USB, DB9, 8 Outlets

MODEL NUMBER: SMX1500LCD





Description

The SMX1500LCD SmartPro 230V 1.5kVA 900W Line-Interactive UPS provides battery backup and AC power protection against blackouts, brownouts, power surges and line noise that can damage electronics or destroy

data. Ideal for backing up home/office workstations, point-of-sale applications, VoIP systems and small business networks, the SMX1500LCD switches to battery mode in milliseconds to keep your connected equipment running long enough to save files and shut down safely with no data loss.

Featuring eight IEC-320-C13 outlets and a C14 inlet that accepts a user-supplied AC power cord, the SMX1500LCD has an internal battery that provides 12 minutes of support at half load and 4.5 minutes at full load. It can also power an entry-level PC up to 60 minutes or a single DVR/VCR component up to three hours. A front-panel LCD screen lets you monitor operating data, such as voltage, battery and overload statuses.

Automatic voltage regulation (AVR) maintains 230V nominal output over an input range of 144V to 282V without using battery power. EMI/RFI noise filtering improves your equipment's performance and prevents damage. An 890-joule surge suppression rating protects your equipment from harmful power surges. With Tripp Lite's free downloadable PowerAlert software, SMX1500LCD enables safe unattended system shutdown and file saves in case of a prolonged power failure.

Features

Protects Mission-Critical Equipment

- Provides fully regulated AC output for home/office workstations, point-of-sale applications, VoIP systems and small business networks
- Audible alarm signals loss of utility power, low battery or overload
- 8 C13 outlets
- C14 inlet accepts user-supplied AC power cord with country-specific plug
- 890-joule surge suppression rating

Reliable Battery Backup

- $\bullet\,$ Supports half load up to 12 min. and full load up to 4.5 min.
- Powers entry-level PC up to 60 min. and a DVR/VCR component up to 3 hr.

Highlights

- Corrects under- and overvoltages from 144V to 282V
- 8 C13 outlets
- Interactive LCD monitoring screen
- Monitoring of power conditions
 via PowerAlert software
- 12 min. runtime at half load; 4.5 min. at full load

Package Includes

- SMX1500LCD SmartPro 230V
 1.5kVA 900W Line-Interactive
 LIPS
- USB cable
- RJ11 cable
- Coaxial cable
- (2) C13-to-C14 power cables
- Tower/rack mounting hardware
- Owner's manual



- Internal batteries designed for hot-swap field replacement
- 96% line-power efficiency rating saves money in energy costs
- Cold-start capability enables turn-on in battery mode during blackouts

Automatic Voltage Regulation (AVR)

• Maintains 230V nominal output over input range of 144V-282V without using battery power

EMI/RFI Line Noise Filtering

• Removes electromagnetic and radio frequency interference that can disrupt or damage equipment's performance

Interactive LCD Screen

- Front-panel LCD signals voltage, battery and overload statuses
- Rotates for easy viewing in rack-mount or tower configurations

Communications Ports

 USB & Serial ports enable data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from www.tripplite.com/poweralert

Telephone/Ethernet/Satellite Protection Against Surges

- RJ45 jacks protect phone/DSL/fax/modem/Ethernet network
- 2.2 GHz coaxial jacks protect CATV, satellite or broadcast antenna connections

Specifications

OUTPUT		
Output Volt Amp Capacity (VA)	1500	
Output kVA Capacity (kVA)	1.5	
Output Watt Capacity (Watts)	900	
Nominal Output Voltage(s) Supported	220V; 230V; 240V	
Nominal Voltage Details	230V nominal output in battery mode	
Frequency Compatibility	50 / 60 Hz	
Frequency Compatibility Details	Automatic frequency selection	
Output Voltage Regulation (Line Mode)	-18%, +8%	
Output Voltage Regulation (Battery Mode)	+/- 5%	
Output Receptacles	(8) C13	
Included Output Power Cables	Includes 2 C13 to C14 output power cables.	
Hot-Swap PDU options	PDUBHV10 (2U / 8 C13 outlets)	
Output AC Waveform (AC Mode)	Sine wave	





Output AC Waveform (Battery Mode)	PWM sine wave	
INPUT		
Rated input current (Maximum Load)	4.4A	
Nominal Input Voltage(s) Supported	230V AC	
UPS Input Connection Type	C14 inlet	
UPS Input Connection Description	Attached 15cm line cord with C14 inlet. C14 inlet accepts user-supplied AC power cord with country specific plug.	
Input Circuit Breakers	5.5A	
UPS Input Cord Length (ft.)	0.5	
UPS Input Cord Length (m)	0.2	
Input Phase	Single-Phase	
BATTERY		
Full Load Runtime (min.)	4.5 min. (900w)	
Half Load Runtime (min.)	12 min. (450w)	
DC System Voltage (VDC)	24	
Battery Recharge Rate (Included Batteries)	Less than 4.5 hours from 10% to 90%	
Expandable Runtime	No	
VOLTAGE REGULATION		
Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 144 to 282	
Overvoltage Correction	Input voltages between 245 and 282 are reduced by 12%	
Undervoltage Correction	Input voltages between 177 and 199 are boosted by 14%	
Severe Undervoltage Correction	Input voltages between 144 and 176 are boosted by 30%	
USER INTERFACE, ALERTS & CONTROLS		
Front Panel LCD Display	Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing	
Switches	2 Switches control off/on power status and alarm-cancel/self-test operation	
Alarm Cancel Operation	Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status	
Audible Alarm	Audible alarm indicates power-failure, low-battery and overload status; alarm can be disabled using PowerAlert software	
LED Indicators	Front panel LCD display	
SURGE / NOISE SUPPRESSION		
UPS AC Suppression Joule Rating	890	





UPS AC Suppression Response Time	Instantaneous	
UPS Dataline Suppression	1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet; Coax jacks (1 set)	
EMI / RFI AC Noise Suppression	Yes	
PHYSICAL		
Included Mounting Accessory Description	Pair of mounting ears enable tower and 2-4 post rackmount installation	
Installation Form Factors Supported with Included Accessories	Tower	
Primary Form Factor	Rackmount	
UPS Power Module Dimensions (hwd, in.)	3.5 x 17.25 x 10.5	
UPS Power Module Dimensions (hwd, cm)	8.89 x 43.82 x 26.67	
Rack Height (U Spaces)	2	
Minimum Required Rack Depth (inches)	12.8	
Minimum Required Rack Depth (cm)	32.51	
UPS Power Module Weight (lbs.)	29.4	
UPS Power Module Weight (kg)	13.34	
UPS Shipping Dimensions (hwd / in.)	7.5 x 22.5 x 15.2	
UPS Shipping Dimensions (hwd / cm)	19.05 x 57.15 x 38.61	
Shipping Weight (lbs.)	33.4	
Shipping Weight (kg)	15.2	
UPS Housing Material	ABS	
Minimum Required Rack Depth (mm)	325	
Primary UPS Height (mm)	89	
Primary UPS Width (mm)	438	
Primary UPS Depth (mm)	267	
Shipping Height (mm)	190	
Shipping Width (mm)	572	
Shipping Depth (mm)	386	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
4/5		



AC Mode BTU / Hr. (Full Load)	128		
Battery Mode BTU / Hr. (Full Load)	542		
AC Mode Efficiency Rating (100% Load)	96%		
COMMUNICATIONS			
Communications Interface	USB (HID enabled); DB9 Serial		
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions		
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert Local software at http://www.tripplite.com/poweralert		
Communications Cable	USB and DB9 Serial cabling included		
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications		
LINE / BATTERY TRANSFER			
Transfer Time	2-4 milliseconds		
Low Voltage Transfer to Battery Power (Setpoint)	144		
High Voltage Transfer to Battery Power (Setpoint)	282		
SPECIAL FEATURES			
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported		
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS		
CERTIFICATIONS			
UPS Certifications	CE; Tested to GOST (Russia); Tested to SASO (Saudi Arabia); Meets FCC Part 15 Category A (EMI)		
UPS Certification Details	CE IEC 62040-1-1, 62040-1-2		
WARRANTY			
Product Warranty Period (International)	2-year limited warranty		
Product Warranty Period (Mexico)	2-year limited warranty		
Product Warranty Period (Puerto Rico)	2-year limited warranty		

© 2017 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies